

UHF-103E / UHF-203E

PAIRING INSTRUCTIONS

Although the DOSS UHF-103E and UHF-203E come pre-paired with the included microphone(s), you may need to re-pair the receiver and microphone. In that case, just follow the instructions below.

Step 1

For example, the receiver is in CH1 614.05 MHz

Press the Menu button 3 times to go to CH/Frequencies Adjustment mode.



Step 2:

Press Up/Down buttons to select CH5 627.1MHz



Step 3

Press Menu button one more time to go to IR mode, turn on the UH103E Mic



Step 4

Press UP button to start to transmit IR to the UH103E microphone, place the microphone close to the IR window of the receiver.



Step 5

Both Mic & Receiver should be locked in the same CH5 627.1MHz, repeat the Step 4 if fails.



Step 6

Press Menu button to exit.

Done