

Duracell Conversion Chart

COPPER TOP ALKALINE

Duracell	IEC	Energizer	Varta	Philips	Kodak	Rayovac	Panasonic	Renata	Seiko
AA MN1500	LR6	E91	4206/4006	LR6	KAA	815	AM3	—	—
AAA MN2400	LR03	E92	4203/4003	LR03	K3A	824	AM4	—	—
C MN1400	LR14	E93	4014	LR14	KC	814	AM2	—	—
D MN1300	LR20	E95	4020	LR20	KD	813	AM1	—	—
9V MN1604	6LR61	522	4022	6LR61	K9V	A1604	6AM6	—	—

ULTRA ALKALINE

Duracell	IEC	Energizer	Varta	Philips	Kodak	Rayovac	Panasonic	Renata	Seiko
AA MX1500	LR6	E91/E99	4206/4006	LR6	KAA	815	AM3	—	—
AAA MX2400	LR03	E92	4203/4003	LR03	K3A	824	AM4	—	—
AAAA MX2500	LR8D425	E96	4061	LR61	—	—	—	—	—
C MX1400	LR14	E93	4014	LR14	KC	814	AM2	—	—
D MX1300	LR20	E95	4020	LR20	KD	813	AM1	—	—
9V MX1604	6LR61	522	4022	6LR61	K9V	A1604	6AM6	—	—

ULTRA LITHIUM

Duracell	IEC	Energizer or Ucar	Varta	Kodak	Panasonic	Rayovac/Vidor	Seiko	Sony	Others
CR-V3	—	CR-V3, ELCRV3	—	CR-V3	CR-V3	—	—	—	CR-V3
CR2	CR17355	CR2, ELCR2	CR2	KCR2	CR2	—	—	CR2B	DLCR2, RLCR2
123	CR17345	EL123AP, EL123A	CR123A, V123	K123LA, KL123LA	CR123A	CR123R	—	CR123	DL123A
223	CR-P2	EL223AP, EL223A	VL223	K223L, K223LA	CRP2P	PC223	—	CR2PS	DL223, CR-P2S, CR-P2
245	2CR5	2CR5, EL2CR5	2CR5	KL2CR5	2CR5M	2CR5R	—	2CR5	DL245

SPECIALTY: PHOTO/HOME MEDICAL/CALCULATOR/SECURITY

Duracell	IEC	Energizer or Ucar	Varta	Kodak	Panasonic	Rayovac/Vidor	Seiko	Sony	Philips	Others
PX625A	LR9	EPX625G	625A, V625U, V625PX	KA625, KX625	LR9/H-D	R625, RPX625	625A	—	—	EPX625, EPX625A, KX625, MR9
DL1/3N	CR11108	2L76	CR1/3N	K58L	—	—	—	CR1/3	CR1/3N	—
PX28L	2CR11108	L544, E23A-A23	V28PXL	K28L	—	—	—	—	—	4G13, 7H34, PS28L, 2CR1/3N, 4SR44

Duracell	IEC	Energizer or Ucar	Varta	Kodak	Panasonic	Rayovac/Vidor	Toshiba	Sony	Philips	Others
MN9100/N	LR1	E90	4001	KN	AM5	810-2	LR1G	LR1SG	LR1	MN9100, 114, 810, 910A, 5500, AM5, E90, LR1, N, R1S
7K67/B/J	3LR17	539	4018	KJ	4LR61	RJ-1	4LR61	—	539	867, 1412P, J, V76PX, 7K67

Duracell	IEC	Energizer/Ucar/Eveready	Varta	Kodak	Panasonic	Rayovac/Vidor	Seiko	Sony	Philips	Others
MS76	SR44	EXP76	V76PX	KS76	SP76	RS76	—	—	—	—
PX76A/675A	LR44	A76	V13GA	KA76	LR44	LR44	—	—	—	—
2016	CR2016	ECR2016	CR2016	KCR2016	CR2016, BR2016	KECR2016-1	CR2016	CR2016	CR2016	DL2016, LF-1/4V, KL2016, BR2016
2025	CR2025	ECR2025	CR2025	KCR2025	CR2025	KECR2025-1	CR2025	CR2025	CR2025	DL2025, KL2025
2032	CR2032	ECR2032	CR2032	KCR2032	CR2032, BR2032	KECR2032-1	CR2032	CR2032	CR2032	DL2032, LF-1/2V, KL2032
DL2450	CR2450	ECR2450	CR2450	—	CR2450	CR2450	—	—	—	5029LC
MN21	3LR50	A23	—	—	—	—	—	—	—	—

WATCH

Duracell	IEC	Eveready/Energizer	Varta	Philips	Kodak	Rayovac	Panasonic	Renata	Seiko	Citizen
301/386	SR43	386	V386	—	KS386	386	SR43SW	386	SR43W, SB-B8	280-11
303/357	SR44	303,357	V357, V76PX	357	K576	357, R576	SR44W	357	LR43	—
364	SR60	364	V364	364	KS364	364	SR621SW	364	SB-AG	280-34
377	SR66	377	V377	377	KS377	377	SR626SW	377	SB-AW	280-39
384/392	SR41	392, 384	V392, V384	392	K392, K384	392	SR41SW	362	SB-B1, SB-A1	280-13
389/390	SR54	389, 390	V389, 390	389	KS389, KS390	389	SR1130SW	389	SB-BU, SB-AU	280-15
186AB	LR43	186	V12GA	—	KA43	186-1	LR43	—	—	—
189AB	LR54	186	V10GA	—	KA54	189-1	LR1130	—	—	—

HEARING AID

Duracell	IEC	Eveready/Energizer	Varta	Philips	Kodak	Rayovac	Panasonic	Renata	Seiko
10	PR70	AC10	V10AT	—	—	10AE	PR230H	ZA10	—
13	PR48	AC13/AC13E	V13AT	—	—	13AE	PR13H	ZA13	—
312	PR41	AC312	V312AT	—	—	312AE	PR312H	ZA312	—
675	PR44	AC675	V675AT	—	—	675AE	PR675P	ZA675	—

LANTERN TORCH

Duracell	IEC	Eveready/Energizer	Neda	Varta	Panasonic	Others
MN908	4LR25X	529	908A	—	—	4LR25
MN918	4LR25-2	521	918A	—	—	8LR25
MN1203	4LR61	—	—	4012	3212	706A

DURACELL®

For further details on which battery to use, visit www.duracell.com.au

All efforts have been made to ensure that information is correct prior to publishing in August 2005. Details are subject to change.

