

1 Install the <b>KDView</b> app from the Google Play store here. KDView replaces Fseye.	
<b>2</b> Register an account if the customer doesn't already have one and then login.	
3 Make sure the NVR is connected to the same network as the phone.	
Once you have logged into the account click the "+" icon on the top right of the screen on your phone.	3:10
<ul> <li>On the next page select</li> <li>Digital Video Recorder</li> <li>from the list of options.</li> </ul>	Digital Video Recorder Add wired device
Make sure that <b>Serial Number</b> is highlighted in blue below the NVR name.	Name: Your NVR Serial Number IP/Domain
<ul> <li>Login into your Doss NVR and go to System Setting/Network Setting/ Management Platform then click QR Code to open a screen that shows 3 QR Codes. You will need to use your phone to scan the Fseye QR code, see step 8.</li> <li>Please note that this QR code is unique in each NVR, so be sure to scan the code of the NVR you intend to add to KDView.</li> </ul>	A Setting CR Code Seriel No. Statue R Code Farye Farye Farye Farye Farye Apple Andreid
On your phone, press the <b>square box</b> with a line through it to activate your camera & scan the <b>Fseye QR code</b> from your NVR. You will here a beep and the device ID will be entered into the SN: field.	Serial Number IP/Domain SN: Username: admin
The username will be admin and the password will be the same password as the NVR. The Stream to select is Substream.	Username:     admin       Password:
Finally click <b>Add Device</b> , you will see a message confirming connection success & the NVR will appear on the <b>Device List</b> screen.	ADD DEVICE
IT you see a <b>Device Offline</b> message there may be an issue with your network settings. See our <u>FAQs page</u> for more help.	