

PASSIVE

MULTISWITCH - END OF LINE

MULTISWITCH 2 WIRE 8 OUTPUTS SATELLITE IF

Product Code: MS2X8

FOXTEL: F30941



- For 8 subscribers or 4 IQ subscribers
- Remote powered by satellite receiver
- The IF polarity selection is controlled by the remote voltage provided by the receiver:
 - < 14.5 V = Vertical
 - > 15.5 V = Horizontal

| Specifications | MS2X8 |
|--|----------------------|
| Inputs | 2 |
| Outputs / Subscribers | 8 |
| Through Loss: SAT-IF: 950 ... 2150 MHz | - 2 ... + 1 dB |
| Isolation: Input | ≥ 24 dB [Typ. 26 dB] |
| Isolation: Switching | ≥ 24 dB [Typ. 26 dB] |
| Current Consumption | < 70 mA |
| Capacity (IF Ports) Max | 500 mA |
| Ambient Temperature | - 20 ... + 50 °C |
| Dimensions (W x D x H mm) | 118 x 72 x 19 mm |